

FUNCTION SELECTOR

Use;

Connected to the control unit via the connector, it does not require any cable connection. The LEDs on the right side of the display indicate the fault center in the event of a fault.

Up and Down buttons are kept at the same time to turn off the fault led.

The panel on the left side of the screen allows to change five different operating modes according to the purpose of using the panel. Working types are as follows;

Wait Open – Partial Opening –One Way Output – Automatic operation - Off



Reset: System can be reset with function selector without opening the mechanism cover. The R button is pressed and the yellow LED burn is released; The up and down buttons are pressed simultaneously, the yellow led is go off released. Press the R and Up button simultaneously while all leds are turned on. 3 sec. then the system starts to reset itself.

Key Lock: Activates when R and Up button are pressed simultaneously. Pressing the R and Down button simultaneously.

Function Selector Mechanical Mounting Dimensions

